

Repair Parts for 700-CF, 700S-CF Control Relays

Coils, side mounted contacts and overlapping contacts are available for 700-CF, 700-CFB, 700-CFM, 700-CFZ, 700S-CF, 700S-CFB control relays.

Repair Parts for other components such as relay power contacts, yoke and armature magnets, coil spring, and relay housing are not available for sale for these products.

Note:

The red front mounted auxiliary contact component supplied with 700S-CF, 700S-CFB control relays is not available for replacement in the field. If this component needs to be replaced, order a new 700S-CF relay.

Repair Coils for AC Operated 700-CF and 700S-CF Control Relays

Example: the replacement coil for a 700-CF400D relay is part number **TA473**.

AC Standard Control Voltages			AC Coil Code in Cat. No.	Catalog Numbers Starting With...
				700-CF, 700-CFM, 700-CFB 700S-CF, 700S-CFB
50 Hz	60 Hz	50/60 Hz		Coil Part Number
-	12 V	-	Q	TA006
12 V	-	-	R	TA404
-	24 V	-	J	TA013
24 V	-	-	K	TA407
-	-	24 V	KJ	TA855
32 V	36 V	-	V	TA481
36 V	-	-	W	TA410
42 V	48 V	-	X	TA482
48 V	-	-	Y	TA414
-	-	48 V	KY	TA860
100 V	100..110V	100V	KP	TA861
110 V	120 V		D	TA473
-	-	110 V	KD	TA856
120 V	-	-	P	TA425
127 V	-	-	S	TA428
200 V	200/220V	200V	KG	TA862
-	208 V	-	H	TA049
200... 220V	208..240V	-	L	TA296
-	-	200 -230	KL	TA864
220 V	240 V	-	A	TA474
220..230V	-	-	F	TA441
-	-	230V	KF	TA851
230...240V	-	-	VA	TA440
240V	277 V	-	T	TA480
-	-	240V	KA	TA858
-	347 V	-	I	TA065
-	380 V	-	E	TA067
380..400V	440 V	-	N	TA071
-	-	400 V	KN	TA863
400..415V	-	-	G	TA457
440 V	480 V	-	B	TA475
-	-	440V	KB	TA859
500 V	-	-	M	TA479
550 V	600 V	-	C	TA476

Repair Parts for 700-CF, 700S-CF Control Relays

Repair Coils for Pure DC Conventional DC Operated 700-CF and 700S-CF Control Relays

Example: the replacement coil for a 700-CF400DJ control relay is part number **TA714M**.

Coil Replacement Notes:

1. Some Coil replacement part numbers in this table have been discontinued for sale.
2. Coils are not interchangeable between AC, DC Conventional, DC Electronic or DC Electronic Quick Drop Out Time Relay Designs

DC Standard Control Voltage [V]	DC Coil Code In Cat. No.	Catalog Numbers Starting With
		Coil Part Number
9V	ZR	700-CF 700-CFM 700-CFB 700S-CF 700S-CFB TA766
9V w/Diode	DR	Not Available
12V	ZQ	TA708
12V w/Diode	DQ	Not Offered
24V	ZJ	TA714
24V w/Diode	DJ	TA714M
36V	ZW	TA719
36V w/Diode	DW	Not Available
48V	ZY	TA724
48V w/Diode	DY	Not Available
60V	ZZ	TA774
60V w/Diode	DZ	Not Available
64V	ZB	TA727
64V w/Diode	DB	Not Available
72V	ZG	TA278
72V w/Diode	DG	Not Available
80V	ZE	TA729
80V w/Diode	DE	Not Available
110V	ZD	TA733
110V w/Diode	DD	Not Available
115 V	ZP	TA734
115V w/Diode	DP	Not Available
125V	ZS	TA737
125V w/Diode	DS	Not Available
220V	ZA	TA747
220V w/Diode	DA	Not Available
230V	ZF	TA749
230V w/Diode	DF	Not Available
250V	ZT	TA751
250V w/Diode	DT	Not Available

Repair Parts for 700-CF, 700S-CF Control Relays

Repair Coils for Electronic DC Operated 700-CF and 700S-CF Control Relays

Example: the replacement coil for a 700-CF400EJ control relay is part number **TC714E**.

Coil Replacement Notes:

1. Coils are not interchangeable between AC, DC Conventional, DC Electronic or DC Quick Drop Out Time Contactor Designs

DC Standard Control Voltage [V]	DC Coil Code In Cat. No.	Catalog Numbers Starting With..... 700-CF, 700-CFM, 700-CFB 700S-CF, 700S-CFB
		Coil Part Number
12V	EQ	TC718E
24V	EJ	TC714E
36 – 48V	EW	TC719E
48 – 72V	EY	TC724E
110 – 125V	ED	TC733E
220 – 250V	EA	TC747E

Repair Coils for Electronic DC Quick Drop Out Time Coils for 700-CF and 700S-CF Control Relays

Example: the replacement coil for a 700-CF400QJ control relay is part number **TC714Q**.

Coil Replacement Notes:

1. Coils are not interchangeable between AC, DC Conventional, DC Electronic or DC Quick Drop Out Contactor Designs

DC Standard Control Voltage [V]	DC Coil Code In Cat. No.	Catalog Numbers Starting With 700-CF, 700-CFM, 700-CFB 700S-CF, 700S-CFB
		Coil Part Number
12V	QQ	TC718Q
24V	QJ	TC714Q
36 – 48V	QW	TC719Q
48 – 72V	QY	TC724Q
110 – 125V	QD	TC733Q
220 – 250V	QA	TC747Q

Repair Parts for 700-CF, 700S-CF Control Relays

Repair Parts for Overlapping Side Mounted Contact Block Supplied with 6 and 8 Pole 700-CF Control Relays

Catalog Number Starting With..	Overlapping Side Mounted Contacts Configuration		Part Number for Contact Block on Right Side	Part Number for Contact Block on Left Side
	N.O.	N.C.		
700-CFZ1510	1	1	100-SAL11 (1 late break N.C. and 1 early make N.O.)	None
700-CFZ1420	1	1		
700-CFZ1330	1	1		
700-CFZ2620	2	2	100-SAL11 (1 late break N.C. and 1 early make N.O.)	100-SAL11 (1 late break N.C. and 1 early make N.O.)
700-CFZ2530	2	2		
700-CFZ2440	2	2		

Repair Parts for Standard Side Mounted Supplied with 6 and 8 Pole 700-CF Control Relays

Catalog Number Starting With..	Standard Side Mounted Contacts Configuration		Part Number for Contact Block on Right Side	Part Number for Contact Block on Left Side
	N.O.	N.C.		
700-CFZ0510	1	1	100-SA11 (1 N.O. – 1 N.C.)	None
700-CFZ042	1	1		
700-CFZ0330	1	1		
700-CFZ0620	2	2	100-SA11 (1 N.O. – 1 N.C.)	100-SA11 (1 N.O. – 1 N.C.)
700-CFZ0530	2	2		
700-CFZ0440	2	2		